

WilsonPro A500

Signal Booster Kit for Homes



A500

The WilsonPro A500 (50 Ohm) from Wilson Electronics is the most popular home and small office cell phone signal booster we currently offer. It features a graphical uplink & downlink meter and self-optimizing design for easy install & maintenance.

- Boosts 3G & 4G for any home or building up to 500m²
- Our most popular home and small office booster
- Works for any phone using Major Network providers in Africa
- Complete kit: all parts included, easy install
- Better voice, text & internet guaranteed



ELECTRICAL SPECS

| | | | | |
|-----------------|---------|-------------------|-----------------------|-----------------------|
| Item No. | A500 | | | |
| Frequency Bands | MHz | 880-915 / 925-960 | 1710-1785 / 1805-1880 | 1920-1980 / 2110-2170 |
| Gain UL/DL | dB | 64 / 66 | 65 / 65 | 74 / 51 |
| Impedance | ohm | 50 | | |
| Input Power | V and A | 5 V / 4 A | | |

MECHANICAL SPECS

| | | | | |
|----------------|----------|----------------------|--|--|
| Connector Type | N-Female | | | |
| Dimensions | cm | 22.23 x 21.59 x 5.72 | | |
| Weight | kg | 0.85 | | |
| Booster Colour | Grey | | | |

With up to +70 dB gain of power, it greatly enhances 4G LTE and 3G cell service for all your wireless cellular devices (smartphones, tablets, notebooks, hotspots, etc.) on any network provider in Africa. There are no monthly fees nor does it need to be connected to any internet source (wifi or landline) to work. It simply amplifies your existing in-building cellular service up to 32X for better voice, text, and faster internet. Backed by a 1-year manufacturer warranty, technical support team in Africa, 30-day better signal or money back guarantee, and lifetime technical support.

Goodbye, no-signal frustrations



QUESTIONS? CALL US TODAY
1-800-568-2723



support@techlineglobal.com



www.techlineglobal.com

